H5NF-T



Tunable N Female with gas barrier for 7/8 in HJ5-50 air dielectric cable

OBSOLETE

Replaced By:

H5PNF Type N Female with gas barrier for 7/8 in HJ5-50 air dielectric cable

Product Classification

Product Type Air coaxial connector

Product Brand HELIAX®

General Specifications

Body Style Straight

Cable Family HJ5-50

Gas Barrier Yes

Inner Contact Attachment Method Self-tapping

Inner Contact Plating Silver

InterfaceN FemaleMounting AngleStraightOuter Contact Attachment MethodTab-flareOuter Contact PlatingUnplated

Dimensions

 Length
 208.026 mm | 8.19 in

 Diameter
 35.814 mm | 1.41 in

Nominal Size 7/8 in

Electrical Specifications

COMMSCOPE®

H5NF-T

Insertion Loss, typical 0.05 dB

Average Power at Frequency 0.6 kW @ 900 MHz

Cable Impedance50 ohmConnector Impedance50 ohmdc Test Voltage2 kV

Insulation Resistance, minimum 5000 MOhm

Operating Frequency Band 0 - 5200 MHz

Peak Power, maximum 10 kW RF Operating Voltage, maximum (vrms) 707 V

VSWR/Return Loss

Frequency Band	VSWR	Return Loss (dB)
1700-2300 MHz	1.12	25
2300-2700 MHz	1.12	25

Environmental Specifications

Operating Temperature $-40 \,^{\circ}\text{C}$ to $+150 \,^{\circ}\text{C}$ (-40 $^{\circ}\text{F}$ to $+302 \,^{\circ}\text{F}$)

Storage Temperature $-70 \,^{\circ}\text{C}$ to $+100 \,^{\circ}\text{C}$ (-94 $^{\circ}\text{F}$ to $+212 \,^{\circ}\text{F}$)

Packaging and Weights

Weight, net 0.93 kg | 2.05 lb

* Footnotes

Insertion Loss, typical 0.05v⁻freq (GHz) (not applicable for elliptical waveguide)

