

FVV-65A-3XKIT



Tri-sector solution that includes 3 FVV-65A-R3-V1 antennas and mounting kit to install them on a pipe

- Suitable for attachment to 3.5-6.5 in or 89-165 mm outer diameter pipe
- Compatible with canister concealment shrouds with inner diameter > 23.5 in (597mm)
- Minimum shroud diameter is the same for all applicable pipe diameters

General Specifications

Band	Multiband
Performance Note	Outdoor usage
RF Connector Interface	4.3-10 Female
RF Connector Location	Bottom
RF Connector Quantity, mid band	12
RF Connector Quantity, low band	6
RF Connector Quantity, total	18

Dimensions

Net Weight, with mounting kit	107 kg 235.894 lb
--------------------------------------	---------------------

Electrical Specifications

Operating Frequency Band	1695 – 2690 MHz 617 – 894 MHz
---------------------------------	---------------------------------

Packaging and Weights

Width, packed	601 mm 23.661 in
Depth, packed	1027 mm 40.433 in
Length, packed	1869 mm 73.583 in
Weight, gross	135.5 kg 298.726 lb

* Footnotes

Performance Note	Severe environmental conditions may degrade optimum performance
-------------------------	---